

MICROPHONE / AERIAL INSTALLATION MICROPHONE / CONDENSER

# FCM-812

UNIDIRECTIONAL AERIAL INSTALLATION CONDENSER MICROPHONE



- ✓ Capturing ambient sound
- ✓ Minimal visual impact
- ✓ Stainless steel hanger
- ✓ Anti-glare black finish

ESPECIALLY RECOMMENDED IN:

Centers of  
Worship

Education



Offices



+ Info:

<https://fonestar.com/FCM-812>

## DESCRIPTION

Hanging electret condenser microphones for stages, choirs, etc.

## TECHNICAL CHARACTERISTICS

|             |                                                                                                                                                                                                                                                                                                      |
|-------------|------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| FEATURES    | Hanging microphone with hypercardioid directivity, especially for environments that are noisy or where the microphone is located far from the sound source, for stages, choirs, etc.<br>Ambient sound pick-up.<br>Easily goes unnoticed.<br>Stainless steel hanger.<br>Anti-reflecting black finish. |
| CAPSULE     | Hypercardioid unidirectional electret condenser.                                                                                                                                                                                                                                                     |
| RESPONSE    | 50-16,000 Hz                                                                                                                                                                                                                                                                                         |
| SENSITIVITY | -34 dB $\pm$ 3 dB (V/Pa) at 1 kHz                                                                                                                                                                                                                                                                    |
| IMPEDANCE   | 250 Ohm $\pm$ 30% at 1 kHz                                                                                                                                                                                                                                                                           |
| CABLE       | 9.5 m fixed cable with male XLR connector (with preamplifier)                                                                                                                                                                                                                                        |
| PHANTOM     | 9 to 52 V DC                                                                                                                                                                                                                                                                                         |
| DIMENSIONS  | 8 mm $\varnothing$ x 121 mm length                                                                                                                                                                                                                                                                   |
| WEIGHT      | 0.2 kg                                                                                                                                                                                                                                                                                               |
| ACCESSORIES | Protective case, hanging support and windshield                                                                                                                                                                                                                                                      |



+ Info:  
<https://fonestar.com/FCM-812>